

**Important: Read all instructions prior to installation.**

## Commercial Can Retrofit LED Down Light




DCL8D-x40

### Safety and Notes

- Product should be installed by a certified electrician in accordance with applicable national, state, and local building and electrical codes.
- To reduce the risk of electric shock, ensure that main power source and circuit breakers are switched off before performing any installation or wiring procedures.
- Avoid looking directly into lamp when illuminated.
- Ensure all mounts are securely attached and will support weight of the fixture. Failure to properly support the fixture may result in damage or injury, for which the manufacturer does not assume responsibility.
- For indoor use only. Suitable for installation in damp locations. Avoid direct contact with water and other liquids.
- Clean with a soft damp cloth only, do not use any chemical cleaners.
- This light should only be installed in an existing fixtures meeting the housing size requirements listed below.

### Housing Compatibility



Model No.	A	B	C
DCL10D-x40	10.05 in. (255 mm)	11.65 in. (296 mm)	9.53 in. (242 mm)
DCL8D-x40	7.9 in. (201 mm)	9.53 in. (242 mm)	8.45 in. (215 mm)

Check product label for specific electrical specifications related to installation. Improper installation will void warranty.

### Installation

1. Remove supply power.
2. Remove and discard existing bulb and reflector from mounting frame.
3. Bypass ballast and remove/cap any unused wiring.
4. Connect supply wires to driver, connect conduit, and mount driver.

Note: In many cases, driver can simply be placed above ceiling. Check codes for proper installation.

5. Dimming use requires Triac dimmers only.
6. Install 3 retaining clips on mounting frame and insert light.

