superbrightleds.com

User Manual

JBL-JL

Important: Read all instructions prior to installation.

Jeep Wrangler JL LED 3rd Brake Light

Included Parts

(1) Jeep Wrangler JL LED 3rd Brake Light

Specifications

Fitment	2018+ Jeep Wrangler JL
Operating Voltage	12 VDC
IP Rating	IP67 waterproof
Warranty	2-year
Aprox. Dimensions[1] (H x W x D)	1.4 x 6.3 x 2.4 in. (36 x 160 x 61 mm)

Pre Installation Instructions

1. Read all safety notes and mounting guidelines before installing the product.
2. Verify that all parts are present and complete.
3. Verify that all power supply and charging systems comply with the specified voltage limits for the light.
4. Ensure your vehicle is parked on a smooth, level surface, turn off the vehicle, and disconnect the battery.

Installation Instructions

1. If your vehicle has a backup camera, locate the plastic cover and use your T40 Torx bit and driver to turn the locking screw to the “unlocked’ position. Then remove the cover.

2. Use the locking lug key, 7/8” SAE socket and 1/2” drive ratchet to remove the lug nuts from the spare tire. Hold the spare tire securely in place while remove the lug nuts, then remove the tire.

3. Place the fender cover (or alternative) over the tailgate and use the T25 Torx bit to remove two (2) long and five (5) short Torx screws from the brake light bracket assembly. Note the location of the long screws at the bottom of the bracket for re-installation.

4. Remove the cover from the back of the bracket assembly and lay it on the fender cover to access the brake light assembly.

5. Use the T25 bit to remove the two (2) Torx screws holding the light assembly in place, squeeze the locking tab on the back of the connector, and remove the connector from the assembly.

Required Tools[2]

- 7/8” SAE socket
- 1/2” drive ratchet
- T25 Torx bit
- 1/4” drive bit driver or ratchet[3]
- T40 Torx bit[3]
- Locking lug key[4]
- Fender cover, towel, or blanket

Pro Tips: Retain all lug nuts and screws in a safe location for reinstallation.

6. Plug the wire connector into the LED 3rd Brake Light.

7. Reconnect the battery and apply power to test functionality.

8. Reverse steps 1-5 to complete installation.

[1] JBL-JL-3BL only.
[2] Required tools may vary by model and trim level. Subject to change without notice.
[3] May be found in the factory Jeep toolkit.
[4] If equipped with locking lug nut.